

## COCO-MODO-V / A MULTI VOLTAGE V/MICRO JUNCTION BOX FOR RED KOMODO

### USER MANUAL

-

**WE STRONGLY RECOMMEND THAT YOU READ THIS INSTRUCTION BEFORE USING YOUR BEBOB RED KOMODO-VMICRO ADAPTER! PLEASE KEEP THIS MANUAL FOR FUTURE REFERENCE**



### Features

- Mounts onto the back of the RED KOMODO
- 5 Outputs (1x USB A, 1x USB C, 1x DTap, 2x Lemo 2p)
- 1x Lemo 2p Input for Hotswap
- On-Off switch incl. LED for the accessories (5 outputs)
- Only one LED

### Hotswap functionality

- Plug an external 7 – 17V DC power source into the Lemo 2p (only input) to swap the battery (Vmount or Goldmount) without interruption



## Safety instructions

- Only for professional use! Keep the COCO-MODO-V/A out of reach of children and personnel that has not been instructed in the use!
- Use only with recommended batteries.
- Keep the COCO-MODO- V/A dry and do not immerse in water.
- Do not attempt to open or repair the COCO-MODO-V/. Contact your dealer for help if it becomes defective.
- Handle with care! Do not throw! Do not drop!
- Remove the battery from the COCO-MODO- V/A when not in use for a longer period of time

## Warranty

- The COCO-MODO-V / A is covered by a 2 years unconditional warranty on all parts.
- For warranty issues or if you have any additional questions, please contact the appropriate bebob distributor listed at [www.bebob.de](http://www.bebob.de).

## Specifications

|                       |  |
|-----------------------|--|
| Model                 | COCO-MODO- V / A                             |
| Battery Mount         | Vmicro (or Amicro)                           |
| Voltages              | 5,0V/14,4V unreg. OUT / 7 to 17V (Camera IN) |
| Max. Draw             | Depends on battery                           |
| Twist D-Tap           | 1 (14,4V unreg. / max. 5.0A)                 |
| USB-A Port            | 1 (5,0V / max. 2,0A)                         |
| USB-C Port            | 1 (5,0V / max. 1,0A)                         |
| Lemo 2p               | 2 (12V unreg. / max. 2,0A)                   |
| Lemo 2p DC IN         | 1 (7 to 17V) Hotswap                         |
| Operation Temperature | 0°C – 40°C                                   |
| Dimensions (WXHXD)    | 66 x 82,2 x 26,1 (mm)                        |
| Weight                | 0,225 kg                                     |