



COCO-15V III MULTI VOLTAGE V-MOUNT JUNCTION BOX

User Manual

WE STRONGLY RECOMMEND THAT YOU READ THIS INSTRUCTION BEFORE USING YOUR BEBOB COCO-15V III ADAPTER! PLEASE KEEP THIS MANUAL FOR FUTURE REFERENCE

Features

- Integrated 15mm Bridge for Horizontal, Vertical and Diagonal use on 15mm Rods
- Multi Voltage 5,0V, 7,6V, 8,4V, 12,0V unreg.
- 8 Outputs (2x USB, 1 Lemo 2p, 2 Twist Dtap, 3 Hirose 4p)
- Main On-Off Switch with led

Safety instructions

- Only for professional use! Keep the COCO-15V III out of reach of children and personnel that has not been instructed in the use!
- Use only with recommended batteries.
- Keep the COCO-15V III dry and do not immerse in water.
- Do not attempt to open or repair the COCO-15V III. Contact your dealer for help if it becomes defective.
- Handle with care! Do not throw! Do not drop!

Warranty

- The COCO-15V III is covered by a 2 years unconditional warranty on all parts.
- For warranty issues or if you have any additional questions, please contact the appropriate bebob distributor listed at www.bebob.de.

Specifications

Model	COCO-15V III
Material	Aluminium
Battery Mount	V-Mount
Voltages	5,0V/7,6V/8,4V/12,0V unreg.
Max. Draw	Depends on battery
Twist D-Tap	2 (14,4V unreg. / max. 5.0A) Self-reset Fuse
USB Port	2 (5,0V / max. 1,0A) Self-reset Fuse
Hirose HR4	3(5,0V/7,6V/8,4V/12,0V unreg. / max. 2,0A) Self reset Fuse
Lemo 2p	1 (14,4V unreg. / max. 2,0A) Self reset Fuse
Dimensions (WXHxD)	90x 160 x 42mm
Weight	0,41 Kg