



AS2MICRO Portable simultaneous li-ion battery charger

User Manual

WE STRONGLY RECOMMEND THAT YOU READ THIS INSTRUCTION BEFORE USING YOUR BEBOB AS2MICRO CHARGER! PLEASE KEEP THIS MANUAL FOR FUTURE REFERENCE

Features

- 2 Channel AMount simultaneous Li-Ion Charger.
- AC Adapter. 16,8V – 5.0A DC Dtap (male) Output
- Powerbase Mode.

Charging

- Never leave batteries unattended while charging
- Plug the blue Dtap Plug of the S1micro in the blue Twist Dtap Socket of the Powerbase-Amicro.
- The S1micro led indicator show green when the charger is plugged in with no battery connected
- The Channel Status indicator turns red when a battery is placed on the corresponding channel and the charging process has begun
- The Channel Status indicator turns back green when the battery is fully charged

AC Adapter S1MICRO

- You can use your S1micro AC Adapter (Part of the Kit) as a 1 Channel Travel Quick Charger
- Plug the Blue Dtap in the Twist Dtap Socket on any bebob battery (but Bmount)
- The AC adapter delivers up to 5,0A under 16,8V

Powerbase

- Plug off the S1micro from the Powerbase-Amicro
- Place one or two full batteries on the Powerbase
- Battery Power will be available over the black twist Dtap Socket
- Maximum Load depends on the batteries and limited to 10A

Safety instructions

- Only for professional use! Keep Charger out of reach of children and personnel that has not been instructed in the use!
- Use only with recommended batteries.
- Keep the charger dry and do not immerse in water.
- Do not cover the charger under use
- Do not keep in contact with any part of the body while the charger is in working status.
- Do not use or store the charger in unstable, dusty or damp environments.
- Remove the battery from the charger after the charging process is complete.
- Do not attempt to open or repair the charger. Contact your dealer for help if it becomes defective.
- Handle with care! Do not throw! Do not drop!

Warranty

- The AS2micro is covered by a 2 years unconditional warranty on all parts.
- For warranty issues or if you have any additional questions, please contact the appropriate bebob distributor listed at www.bebob.de.

Specifications

Model	AS2micro
Mount	Amicro
Channel	2 simultaneous
Charging current	16,8V 2.5A per Channel 5,0A global
AC In	90-264V/47-63Hz 100W
Weight AC Adaptor	0,365 Kg
Dimensions (WXHxD)	40 x 138x 60mm
Weight Powerbase	0,160 Kg
Dimensions (WXHxD)	96 x 66x 45mm
Batteries	bebob
Charging time	depends on the battery capacity
Operating Temp. Range	- 10°C ~ + 35°C